# **MB010 Xenon Strobe Beacon**



The MB010 is a 10 Joule Xenon strobe beacon featuring a robust, fire retardant, IP66 & IP67 housing; suitable for harsh environments.

## Features


- Automatic synchronised flash, or Flip-Flop alternating mode.
- Xenon tube mechanically secured against vibration.
- Continuously rated.
- Large termination area.
- Stainless steel fixings.
- Ratchet adjustable stainless steel 'U' bracket for 360° positioning.
- Duplicate cable terminations (in & out for daisy-chain installations).
- Tropicalised as standard.

## **Approvals**

• GOST-R approved. Cert: POCC GB.JB05.H00144.

ϥ (€ [f][





## Specification

Energy:	10 Joules (10Ws)		
Flash rate:	1Hz (60 fpm)		
Peak Candela:	1,000,000 cd - calculated from energy (J)		
Effective Intensity cd:	500 cd - calculated from energy (J)		
Peak Candela:	43,920 cd* - measured ref. to I.E.S.		
Effective Intensity cd:	183 cd* - measured ref. to I.E.S.		
Lens colours:	Amber, Blue, Clear, Green, Red & Yellow		
Voltages DC:	12V dc; 24V dc; 48V dc		
Voltages AC:	115V ac; 230V ac		
Ingress protection:	: IP66 & IP67 (Third party tested)		
Housing material:	High impact UL94 VO & 5VA FR ABS		
Colour:	Grey (RAL7038)		
Cable entries:	2 x M20 supplied with 1 blanking plug		
Lens material:	Borosilicate glass dome with PC prismatic lens cover.		
Guard:	Stainless Steel dome guard as standard		
Terminals:	0.5 to 4.0mm <sup>2</sup> cables.		
Operating temp:	-25 to +55°C [-13 to +131°F]		
Storage temp:	-40 to +70°C [-40 to +158°F]		
Relative humidity:	90% at 20°C [68°F]		
Weight:	1.48kg/3.25lbs		
*Candola moscuror	monte representative of performance with clear long at		

\*Candela measurements representative of performance with clear lens at optimum voltage.

# Part Codes

Version:	Part code:	
12V dc	MB010DC12G-[xx]	
2 4V dc	MB010DC24G-[xx]	
48V dc	MB010DC48G-[xx]	
115V ac	MB010AC115G-[xx]	
2 30V ac	MB010AC230G-[xx]	
[xx] = Lens colour:	AM: Amber, BL: Blue, CL: Clear, GN: Green, RD: Red, YW: Yellow	

Also available as the MCA112-05 combined alarm sounder and Xenon beacon and the MCL15-05 15W PA Loudspeaker with Xenon beacon.

## **Current Consumption**

Version:		Voltage:	Current mA:
12V dc		10-14V dc	1.45A
2 4V dc		2 0-2 8V dc	660mA
48V dc		42-54V dc	340mA
115V ac	50/60Hz	+/-10%	250mA
2 30V ac	50/60Hz	+/-10%	110mA

# AUTHORIZED DISTRIBUTOR: GasDetectorsUSA.com Houston, Texas USA sales@GasDetectorsUSA.com 832-615-3588