BExCBGL2-L2 Explosion Proof Dual LED Beacon



The flameproof BExCBGL2-L2 dual LED beacons are suitable for Zone 1, 2, 21 & 22 applications. Approved to IECEx and ATEX standards.

The BExCBGL2-L2D dual LED beacons robust construction enables installation in the harshest of environments. The beacons may be connected from a single supply for simultaneous operation or from separate supplies for independent operation.

The BEx range features enclosures manufactured from corrosion proof, marine grade copper free LM6 aluminium with a chromate and powder coat finish. All models have two M20 cable entries, large termination areas containing in & out terminals and an ingress protection of IP66/67.

Features

- Marine grade, corrosion proof, LM6 aluminium enclosure
- Automatic synchronisation on multi-beacon system.
- Beacons can be set to 'flip-flop' alternating mode with other units on multi-beacon systems.
- Xenon tubes mechanically secured against shock & vibration
- Glass lens & Stainless Steel guard
- Very large termination area.
- Dual M20 cable entries adaptors available.
- Stopping plug included.
- Ratchet adjustable stainless steel 'U' bracket.
- Reverse polarity diode fitted.
- IP66/67 ingress protection.
- 160+160 candela effective light intensity.
- UV stable PC, field replaceable, colour lens filters.

Approvals

- IECEx KEM 10.0024X
- ATEX KEMA QOATEX2222X
- TR-CU Ex EAC certificate: RU C-GB.AA71.B.00109
- INMETRO certificate: IEx 19.0092X

Coding

- II 2G Ex d IIB T6 Gb Ta. -50°C to +55°C
- II 2G Ex d IIB T5 Gb Ta. -50°C to +70°C
- II 2D Ex tb IIIC T65°C Db Ta. -50°C to +40°C
- II 2D Ex tb IIIC T80°C Db Ta. -50°C to +55°C
- II 2D Ex tb IIIC T95°C Db Ta. -50°C to +70°C




















Specification

Specification				
Source:	Dual arrays of 4 x High Power Cree® LED's			
Modes:	1Hz flash (60 fpm) 1.5Hz flash (90 fpm) 2Hz flash (120 fpm) Double strike flash Triple strike flash High Power Steady Low Power Steady			
Eff. Intensity cd:	87 cd - High Power Steady (each beacon)			
Eff. Intensity cd:	160 cd - 1Hz flash (each beacon)			
Lens colours:	Amber, Blue, Clear, Green, Magenta, Red & Yellow			
Voltages DC:	24vdc			
Voltages AC:	115vac; 230vac			
Ingress protection:	IP66/67			
Enclosure matl:	Marine grade copper free LM6 Aluminium			
Enclosure finish:	Chromate & powder coated finish – anti-corrosion.			
Colour:	RAL3000 Red (others available on request)			
Cable entries:	Dual M20 ISO (one stopping plug inc)			
Terminals:	0.5 - 2.5mm² (20·14 AWG)			
Enclosure volume:	<2 litres			
Line monitoring:	Blocking diode included EOL Min. 500 Ohm 2w, or 3k3 Ohm 0.5w resistor or diode (DC versions) can be fitted			
Grounding stud:	M5			
Temperature range:	-50° to +70°C (-58°F to +158°F)			
Relative humidity:	95% – Additional tropicalisation is recommended for applications where both high relative humidity and high ambient temperatures exist			
LED life:	60,000 hours			
Weight:	DC: 4.00kg/8.8lbs AC: 4.35kg/9.57lbs			
*All candela data i optimum voltage.	s representative of performance with clear lens at			

Part Codes

Part Codes					
Version: Product type:	Part code: BExCBGL2L2	Explosion proof Dual LED Beacon			
Type:	DP	Ex d, UV stable PC Colour Lenses			
Voltage:	DC024 AC115 AC230	24V dc 115V ac 240V ac			
Cable Entry Type: [e]	A B C D E F G	2 x M20x1.5mm 2 × 1/2" NPT – adaptors 2 × 3/4" NPT – adaptors 2 x M25x1.5mm – adaptors 1 × 1/2" NPT – adaptor 1 × 3/4" NPT – adaptor 1 x M25x1.5mm – adaptor			
Adaptor/Stopping plug material: [m]	B N S	Brass Nickel Plated Stainless Steel			
Bracket/guard matl & tag: [s]	1 2 3 4	A2 304 Stainless Steel A4 316 Stainless Steel A2 304 St/St with Equip. Tag A4 316 St/St with Equip. Tag			
Product version: [v]A1	Default – IECEx, ATEX			
Enclosure colour: [x]	R S	Red RAL3000 Special – contact E2S			
1st LED lens colour: [y] 2nd LED lens colour: [y]	A B C G M R Y	Amber Blue Clear Green Magenta Red Yellow	A Amber B Blue C Clear G Green M Magenta R Red Y Yellow		

Current Consumption

Version:	Voltage:	Steady High Power:	Steady Low Power:	Flashing 1Hz:		
24V dc	18-54V dc	240mA	134mA	110mA		
115V ac	103.5-126.5V ac 50/60Hz	95mA	78mA	90mA		
230V ac	207-253V ac 50/60Hz	48mA	37mA	45mA		
Current listed per beacon						

E2S Warning Signals sales@e2s.com www.e2s.com

Multi-function patterns

14 Sep 2019

[On board]

[Remote] Steady High Power Flashing 1Hz

ent. All dimensions are approximate. This unit is sold subject to our standard [Remote] Triple Strike